



Your Phone

- (1) Handset
- (2) Base Station
- (3) Charger Cradle
- 4 Call history
- (5) Line Status
- 6 Place internal call
- 7 Directory
- (8) Decrease ringer volume
- (9) Increase ringer volume

Basic Operations

Turning Handset On/Off:

- \bullet Press $\ensuremath{\overline{\bullet}}$, then the LCD screen lights up.
- Place the Handset in the charger cradle to turn on automatically.
- Long press 🕤 again to turn the Handset off.

Locking/Unlocking keypad:

- Long press # when the Handset is idle to lock the keypad.
- Long press # a again to unlock the keypad.

Switching Silent Mode On/Off:

- Long press ** when the Handset is idle to lock the keypad.
- Long press ** again to unlock the keypad.

Access the Directory

 Press the **OK** key to enter the main menu, and then select **Directory**.

To add a contact

- Press the **OK** key to enter the main menu, and then select **Directory**.
- 2. Press the **Options** soft key, and then select **New Contact.**
- Enter the desired values in the Name, Number and Mobile fields.
- 4. Press the **Save** soft key to accept the change.

To edit a contact

- Press the **0K** key to enter the main menu, and then select **Directory.**
- 2. Press or to highlight the desired entry.
- 3. Press the ${\bf Options}$ soft key, and then select ${\bf Edit.}$
- 4. Edit the values in the ${\bf Name, Number}$ and ${\bf Mobile}$ fields.
- 5. Press the **Save** soft key to accept the change.

To delete a contact

- Press the **OK** key to enter the main menu, and then select **Directory.**
- 2. Press or to highlight the desired entry.
- 3. Press the **Options** soft key, and then select **Delete** to delete the selected entry.

Make a Call

Enter the desired number when the handset is idle, and then $\operatorname{pr}(s)$.



YEALINK DECT PHONE W52P Quick Start Guide

To place a call from the local directory

- 1. Press (when the handset is idle.
- 2. Press or to highlight the desired entry, and then then press .

If both the office number and mobile number are stored, press • or • to highlight.

the desired number, and then press [7] again.

Answer a Call

Press the Accept soft key.

Put a Call on Hold

- 1. Press the **Options** soft key during a call, and then select **Hold**.
- 2. If there is only a call on hold, press the **Resume** soft key.

Transfer a Call to Another Person

- Press the **Options** soft key during call, and then select Transfer.
- 2. Enter the number you want to transfers the call to.
- 3. Press **Transfer** soft key.

Make a Call with the Speakerphone

- 1. Enter a number using the keypad.
- 2. Press **Speakerphone** .

Mute Your Audio

- 1. Press Mute key.
- 2. Press Mute again to turn mute off.

Listen to Your Voice Messages

Press **Messages** keys and follow the voice prompts. To check messages for a specific line, press the line button first

Adjust the Volume in a Call

Whilst in call, press \triangleleft or \triangleright .

Adjust the Ringtone Volume

Press **◄** or **▶** , whilst

Handset Registration

The handset in the W52P package is pre-registered to the base station. Internal handset number and name display on the idle screen after turning the handset on. If your handset is not pre-registered to the base station, do one of the followings to register it manually:

If the handset LCD screen prompts "Searching for Base", long press
 on the base station till the registration LED flashes. Then press the OK key to enter the main menu, and then select Settings → Registration → Register Handset to register the handset.

• If the handset LCD screen prompts "Press base page 2s then press OK", long press on the base station till the registration LED flashes.

Then press the **OK** soft key on the handset.

Notes